



## Xclaim™ Xi-3

### BUSINESS-CLASS WI-FI ACCESS POINT

#### Dual-Band 2x2 802.11ac indoor access point

Xclaim access points provide superior functionality, elegant simplicity, and competitive pricing for small businesses. The Xi-3 AP is a dual-radio, dual-band concurrent AP utilizing the latest 802.11ac Wi-Fi technology. The Xi-3 AP boasts industry leading Wi-Fi performance with speeds up to 1.167 Gigabits per second making it a perfect fit for dense environments such as classrooms and public venues.

#### BENEFITS

##### Elegant Simplicity

- Controller-free multi-AP architecture
- Completely mobile-app managed
- Automatic AP discovery
- Simple wizard-driven configuration

##### Enterprise Reliability

- Hand-crafted APs from the ground up
- Not based on a standard AP reference design
- Enterprise-grade feature set not found in traditional SMB APs

##### Consumer Affordability

- Affordable enterprise performance
- Free configuration, management and stats app
- No AP Licenses required
- One year Limited Hardware Warranty

# Xclaim™ Xi-3

## BUSINESS-CLASS WI-FI ACCESS POINT

### Big Wi-Fi. Small Business.

Xclaim Access Points allow for next generation Wi-Fi for all your business needs including hotspot access for your guests and secure Wi-Fi for your employees and business data. Xclaim access points are #Mobile ready to support smartphones, tablets, and traditional Wi-Fi products with fast and reliable Wi-Fi connectivity.

### A New Way to Wi-Fi.

Xclaim provides a new way to Wi-Fi. Small businesses no longer have to choose between overly complex and expensive enterprise solutions or low functionality consumer grade products. Xclaim is the complete package, combining reliability and simplicity with leading edge business-class Wi-Fi technology. Xclaim has been uniquely developed and positioned to address the Wi-Fi needs of the small business network.

### Connect. Click. Go.

By downloading the free application, Harmony for Xclaim, you can configure, monitor and manage multiple access points and networks all from your smart device in the palm of your hand. With Harmony, Wi-Fi security is easy: Simply create a separate Wi-Fi network for your secure data and protect it with industry standard enterprise encryption. You can create up to 4 separate Wi-Fi networks (SSIDs) per Access Point, allowing you to support and secure different business requirements on different wireless networks

### Wi-Fi for the Non-IT Guy.

Setup your own secure and reliable Wi-Fi network without requiring expensive cloud services, dedicated appliances or other complicated software. Harmony allows you to quickly setup secure Wi-Fi networks with multiple Xclaim access points in a matter of minutes, leaving you free to focus on your business.

### FEATURES

- Advanced RF design
- Dynamic channel selection (auto)
- Automatic traffic prioritization (auto)
- Airtime Fairness (auto)
- Band Steering (auto)
- Client isolation (per AP)
- Single or multi-AP environments
- 4 SSIDs per AP
- Cloud ready management



**PHYSICAL CHARACTERISTICS**

<b>POWER</b>	<ul style="list-style-type: none"> <li>• DC Input: 12 VDC 1.0A</li> <li>• Power over Ethernet 802.3 af</li> </ul>
<b>PHYSICAL SIZE</b>	<ul style="list-style-type: none"> <li>• 15.8 cm x 15.8 cm x 4 cm (6.2 in x 6.2 in x 1.57 in)</li> </ul>
<b>WEIGHT</b>	<ul style="list-style-type: none"> <li>• 350 g (0.77 lb.)</li> </ul>
<b>ETHERNET PORTS</b>	<ul style="list-style-type: none"> <li>• 1 auto MDX, auto-sensing 10/100/1000 Mbps, RJ-45, POE port (on one port)</li> </ul>
<b>LOCK OPTIONS</b>	<ul style="list-style-type: none"> <li>• Hidden latching mechanism</li> <li>• Kensington Lock Hole</li> <li>• T-bar Torx</li> <li>• Bracket (902-0108-0000) Torx screw &amp; padlock (sold separately)</li> </ul>
<b>ENVIRONMENTAL CONDITIONS</b>	<ul style="list-style-type: none"> <li>• Operating Temperature: 0°C - 50°C</li> <li>• Operating Humidity: 10% - 95% non-condensing</li> </ul>
<b>POWER DRAW</b>	PoE-Powered <ul style="list-style-type: none"> <li>• Idle: 4W</li> <li>• Typical: 5.95W</li> <li>• Peak: 10.5W</li> </ul> 12VDC-Powered <ul style="list-style-type: none"> <li>• Idle: 4W</li> <li>• Typical: 6.13W</li> <li>• Peak: 11.1W</li> </ul>

**PERFORMANCE AND CAPACITY**

<b>CONCURRENT STATIONS</b>	<ul style="list-style-type: none"> <li>• Up to 100 clients</li> </ul>
----------------------------	---

**MANAGEMENT**

<b>DEPLOYMENT OPTIONS</b>	<ul style="list-style-type: none"> <li>• Group or standalone</li> </ul>
<b>CONFIGURATION</b>	<ul style="list-style-type: none"> <li>• Harmony for Xclaim</li> <li>• Recommended for networks up to 10 APs</li> </ul>

**WI-FI**

<b>STANDARDS</b>	<ul style="list-style-type: none"> <li>• IEEE 802.11a/b/g/n/ac</li> <li>• 2.4GHz and 5GHz</li> </ul>
<b>SUPPORTED DATA RATES</b>	<ul style="list-style-type: none"> <li>• 802.11n/ac: 6.5Mbps – 173.4Mbps (20MHz)</li> <li>• 13.5Mbps – 400Mbps (40MHz)</li> <li>• 29.3Mbps – 867Mbps (80MHz)</li> <li>• 802.11a: 54, 48, 36, 24, 18, 12, 9 and 6Mbps</li> <li>• 802.11b: 11, 5.5, 2 and 1 Mbps</li> <li>• 802.11g: 54, 48, 36, 24, 18, 12, 9 and 6 Mbps</li> </ul>
<b>AUTO CHANNEL SELECTION</b>	<ul style="list-style-type: none"> <li>• Supported</li> </ul>
<b>RF POWER OUTPUT</b>	<ul style="list-style-type: none"> <li>• 25 dBm for 2.4GHz†</li> <li>• 25 dBm for 5GHz†</li> </ul>
<b>BSSID</b>	<ul style="list-style-type: none"> <li>• Up to 4</li> </ul>
<b>POWER SAVE</b>	<ul style="list-style-type: none"> <li>• Supported</li> </ul>
<b>WIRELESS SECURITY</b>	<ul style="list-style-type: none"> <li>• WPA-PSK, WPA-TKIP, WPA2 AES</li> </ul>
<b>CERTIFICATIONS</b>	<ul style="list-style-type: none"> <li>• FCC(US), IC (Canada), CE (European countries)</li> </ul>
<b>ANTENNA</b>	<ul style="list-style-type: none"> <li>• Omnidirectional</li> </ul>

† Maximum power varies by country

**Product Ordering Information**

MODEL	DESCRIPTION
<b>Xclaim Xi-3 Business Class Wi-Fi Access Point</b>	
<b>AP-Xi-3-XX00</b>	Xclaim Indoor Dual-Band (2.4GHz & 5GHz Concurrent) 802.11ac Wireless Access Point. 2x2:2 (2 spatial streams). Includes PoE Adapter. For -US00 the US power cord is included. For -WW00 please order separately the required country power cord at no extra cost.
<b>Optional Accessories</b>	
<b>902-0300-XX00</b>	Power cord for PoE Adapter

PLEASE NOTE: When ordering Xclaim Indoor APs, you must specify the destination region by indicating -US, or -WW instead of XX. When ordering PoE injectors or power supplies, you must specify the destination region by indicating -US, -EU, -AU, -BR, -CN, -IN, -JP, -KR, -SA, -UK, or -UN instead of -XX.